



# 1861

## Handheld RFID Reader



# 1861

Designed for warehouse operations, logistics centers, manufacturing plants and retail operations, the CipherLab 1861 is a handheld RFID reader which addresses the growing demand for ultra-high frequency (UHF) RFID applications. The 1861 allows users the freedom to read and write RFID tags from a greater distance, increasing efficiency – the ability to get more done in less time, ultimately reducing costs and strengthening the bottom line.



### Connect to PC for Easy Configuration

The 1861 comes with CipherLab ScanMaster at no extra cost. ScanMaster software offers an easy solution to configure 1861 to suit your specific business needs. It is easy to set up related parameters, also change and edit formats through the standard Windows® operating system in a PC via USB interface.

### Value-added Solution for Mobile Computers

A peripheral device that is used in supplement to *Bluetooth®*-enabled mobile computers, the 1861 allows CipherLab's own 8400 or 9600 series, and other branded mobile computers to snap onto its holder, in order to provide you with additional UHF RFID read/write ability on top of traditional barcode capture. A user can easily switch between RFID tag reading and barcode reading via a reader switch on the 1861; it is thus suited for operations that require extreme flexibility in data acquisition options. Workers are now able to read and write, from ground level, RFID tags in pallets that are stacked high.

### Durable Performance, Non-Stop Productivity

Extensively tested for durability, the 1861 can survive multiple drops onto concrete from 1.5 m (5 ft.), and 1,000 tumbles at 1 m (3 ft.), which ensures continued productivity even in the case of careless falls onto unforgiving surfaces. In addition, it is rated IP64, ensuring protection against harsh environments, such as warehouses, logistics centers, and factories.

### Data Capture via UHF RFID Increases Adaptability

The 1861 meets the latest requirements to adapt RFID technology in warehousing operations, as well as logistics, manufacturing and retail industries. The UHF RFID read/write capability enables data collection from RFID tags via ultra-high frequency, allowing workers to read/write RFID tags from a distance of up to 1 m (3.3 ft.) / 0.5 m (1.6 ft.) to improve productivity significantly.





# 1861

## Handheld RFID Reader



|                          |                               | 1861  |
|--------------------------|-------------------------------|---|
| Performance              | CPU                           | ARM Cortex-M3 32 bit  |
|                          | Memory                        | 4 MB  |
|                          | Operating power               | Rechargeable 3.7V 2500 mAh Li-ion battery   |
|                          | Working hours*1               | 10 Hours  |
|                          | Alert                         | Tri-color LEDs (red / blue / green), vibrator, beeper   |
| Wireless Communication   | WPAN                          | Bluetooth® V2.1 + EDR class 2   |
|                          | Bluetooth® profile            | SPP Slave, Master   |
| RFID Data Capture        | Frequency                     | 865 ~ 868 MHz / 902 ~ 928 MHz / 952 ~ 954 MHz   |
|                          | Max. Reading / Writing range* | 1 m (3.3 ft.) / 0.5 m (1.6 ft.)   |
|                          | Antenna type                  | Linear polarized  |
|                          | Support tags                  | EPCglobal UHF Gen 2, ISO 18000-6c   |
|                          | Output power                  | 24 dBm  |
| Physical characteristics | Keys                          | 2 function keys, 1 trigger key, 1 toggle switch   |
|                          | Dimensions (L x W x H)        | 187.5 x 85.7 x 146.5mm  |
|                          | Weight (including battery)    | 502 g / 17.7 oz.  |
| User environment         | Operating temperature         | -20 °F to 60 °C / -4 °F to 140 °F   |
|                          | Storage temperature           | -30 °F to 70 °C / -22 °F to 158 °F  |
|                          | Humidity (non-condensed)      | Storage 5% to 95% / Operating 10% to 90%  |
|                          | Impact resistance             | Multiple 1.5m / 5 ft. drop onto concrete,<br>5 drops on each side / 1,000 tumbles at 1 m (3.3 ft.) / IP64 |
|                          | Electrostatic discharge       | ± 15kV air discharge / ± 8kV direct discharge   |
|                          | EMC regulation                | FCC, CE, BSMI, NCC  |
| Configuration            |                               | Comes with Windows®-based ScanMaster software for fast and easy customization via USB interface           |
| Accessories              |                               | 3610 Bluetooth® Transponder, Micro USB cable, battery charger, mobile computer holder                     |
| Warranty                 |                               | 1 year  |



ACCESSORIES



Battery Charger

©2012 CipherLab Co., Ltd. All specifications are subject to change without notice. All rights reserved. All brand, product and service, and trademark names are the property of their registered owners.



**HEADQUARTERS**  
CipherLab Co., Ltd.  
12F, 333 Dunhua S. Rd., Sec.2  
Taipei, Taiwan 10669  
Tel +886 2 8647 1166  
Fax +886 2 8732 3300  
www.cipherlab.com

**CipherLab China**  
J Room, 4F, No.728 West Yan'an  
Road, Changning District, Shanghai  
China 200050  
Tel +86 21 3368 0288  
Fax +86 21 3368 0286

**CipherLab USA**  
2552 Summit Avenue  
Plano, Texas USA 75074  
Tel +1 469 241 9779  
Toll Free 888 300 9779  
Fax +1 469 241 0697

**CipherLab Central Europe**  
Willicher Damm 145  
41066 Mönchengladbach  
Germany  
Tel +49 2161 56230 0  
Fax +49 2161 56230 22